

Catalogue No: **KTA9-32S-6P3A**

MOTOR PROTECTION CIRCUIT BREAKER KTA9-32S FRAME C 4.0-6.3A

Motor Control and Drives > Motor Starting and Protection > Motor Protection Circuit Breakers > Sprecher + Schuh Motor Protection Circuit Breakers



Motor Protection circuit breaker 4... 6.3 Amp



- Manual motor starting permits on / off motor control for non-severe duty
- Available in a wide range of motor sizes to suit your installation type
- Wide range of accessories for application flexibility

Representative Photo Only
(actual product may vary based on configuration selections)

SPECIFICATIONS

Product Series	Motor Protection
Component Type Motor Control and Drives	Motor Protection Circuit Breaker
Approx. kW (AC 3, 400/415 V AC)	2.2 kW
kW Rating, AC-3, 415V	2.2 kW @415V
kW Rating, AC-3, 415V, Max	2.2 kW @415V max
Ie, Rated Operational Current, nom	6.3 A,nom
Ir, Thermal Trip Setting, Min	4 A min
Ir, Thermal Trip Setting, Max	6.3 A max
Im, Magnetic Trip Current	88 A
Icu, Rated Ultimate Short-Circuit Breaking Capacity, 400V AC	100 kA @400VAC
Icu, Rated Ultimate Short-Circuit Breaking Capacity, 415V AC	100 kA @415VAC
Ics, Rated Service Short-Circuit Breaking Capacity, 400V AC	100 kA
IP Rating	IP2X

REFERENCES

IECEx Certificate	-
Supplier Declaration of Conformity:	-
Installation Guide:	-
User Manual:	-
Manufacturer Datasheet:	-
Manufacturer Catalogue & Product Selection:	-